

# ***Table of Contents***

---

## **07.01.06 - Rules Governing The Use Of National Electrical Code Division Of Building Safety**

000. Legal Authority. ....	2
001. Title And Scope. ....	2
002. Written Interpretations. ....	2
003. Administrative Appeals. ....	2
004. -- 010. (Reserved). ....	2
011. National Electrical Code, 2002 Edition. ....	2
012. -- 999. (Reserved). ....	2

**IDAPA 07  
TITLE 01  
CHAPTER 06**

**07.01.06 - RULES GOVERNING THE USE OF NATIONAL ELECTRICAL CODE  
DIVISION OF BUILDING SAFETY**

**000. LEGAL AUTHORITY.**

The Idaho Electrical Board is authorized under Section 54-1001, Idaho Code, to adopt rules concerning the use of the National Electrical Code. (2-26-93)

**001. TITLE AND SCOPE.**

These rules shall be cited as IDAPA 07.01.06, "Rules Governing the Use of National Electrical Code," Division of Building Safety. These rules prescribe which edition of the National Electrical Code will be administered by the Idaho Electrical Board. (2-26-93)

**002. WRITTEN INTERPRETATIONS.**

This agency has no written interpretations of this chapter. (2-26-93)

**003. ADMINISTRATIVE APPEALS.**

This chapter does not allow administrative relief of the provisions outlined herein. (2-26-93)

**004. -- 010. (RESERVED).**

**011. NATIONAL ELECTRICAL CODE, 2002 EDITION.**

**01. Documents.** Under the provisions of Section 54-1001, Idaho Code, the National Electrical Code, 2002 Edition, is hereby adopted for the state of Idaho and shall be in full force and effect on and after July 1, 2002, with the exception of Article 80 and the following: (5-3-03)

**a.** Compliance with Article 675.8(B) will include the additional requirement that a disconnecting means always be provided at the point of service from the utility no matter where the disconnecting means for the machine is located. (5-3-03)

**b.** Compliance with Article 550.32(B) shall limit installation of a service on a manufactured home to those homes manufactured after January 1, 1992. (5-3-03)

**c.** Compliance with Article 210.12(B) shall not apply to the fire/smoke alarm branch circuit outlet. (5-3-03)

**d.** A pole that is no more than forty (40) feet in nominal height that supports no more than four (4) luminaires that are operating at a nominal voltage of three hundred (300) volts or less, shall not be considered to constitute a structure as that term is defined by the National Electrical Code (NEC) and no disconnecting means shall be required. Overcurrent protection for wiring within the pole and luminaires mounted to the pole shall be provided by Bussman KTK fast-acting (200KAIC) or equivalent mounted in separable (break-a-way) fuse holders equivalent to the Bussman HEB series with a six hundred (600) volt rating. (Note: for two hundred, eight (208) or two hundred, forty (240) volt installations, the fuse holders require Bussman HEY Series, double-pole or equivalent.) The fuse holder shall be located within the pole itself, and accessible from the hand hole. Any poles supporting or incorporating utilization equipment other than luminaires, and other poles supporting luminaires shall be considered structures, and an appropriate service disconnecting means shall be required (per the NEC). All luminaire-supporting poles shall be appropriately grounded (and bonded per the NEC). All poles supporting luminaires, shall indicate by a permanent warning label to read: Wiring to pole is un-fused, service entrance conductors enclosed within. (11-6-03)T

**02. Availability.** This document is available at the office of the Division of Building Safety, Electrical Bureau 1090 E. Watertower St., Meridian, Idaho. (5-3-03)

**012. -- 999. (RESERVED).**

# ***Subject Index***

## **D**

Documents, National Electrical Code  
Incorporation 2

## **N**

National Electrical Code, 2002  
Edition 2